

> General Description

The PAE0514FGJ provides a typical line to line capacitance of 0.1pF and low insertion loss up to 10GHz providing greater signal integrity making it ideally suited for USB 3.0 applications, such as Digital TVS, DVD players, Computing, set-top boxes and MDDI applications in mobile computing devices.

It has been specifically designed to protect sensitive components which are connected to high-speed data and transmission lines from overvoltage caused by ESD(electrostatic discharge), CDE (Cable Discharge Events), and EFT (electrical fast transients).

> Feature

- Protects four I/O lines and one Vcc line
- Low capacitance
- Working voltages: 5V
- Low leakage current
- Low capacitance (<0.8pF) for high-speed interfaces
- No insertion loss to 10.0GHz
- lacktriangle Response Time is < 1 ns
- Meets MSL 1 Requirements
- Solid-state silicon avalanche technology
- ROHS compliant

Application


- Digital Visual Interface (DVI)
- 10/100/1000 Ethernet
- USB 1.1/2.0/3.0/OTG
- IEEE 1394 Firewire Ports
- Projection TV Monitors and Flat Panel Displays
- Notebook Computers
- Set Top Box
- Projection TV

Protection solution to meet

- IEC61000-4-2 (ESD) ±15kV (air), ±8kV (contact)
- IEC61000-4-4 (EFT) 40A (5/50ns)
- IEC61000-4-5 (Lightning) 4A (8/20 μs)









➤ Maximum Ratings (TA=25°C Unless otherwise specified)

Parameter	Symbol	Value	Unit
Peak Pulse Power (tp=8/20μs waveform)	Pppp	40	Watts
Peak Pulse Current(tp=8/20μs waveform)	Ірр	4	A
ESD Rating per IEC61000-4-2: Contact		20	KV
Air		20	KV
Lead Soldering Temperature	TL	260 (10 sec.)	$^{\circ}$ C
Operating Temperature Range	ΤJ	-55 ~ 150	$^{\circ}$ C
Storage Temperature Range	Tstg	-55 ~ 150	$^{\circ}$ C


Maximum ratings are those values beyond which device damage can occur. Maximum ratings applied to the device are individual stress limit values (not normal operating conditions) and are not valid simultaneously. If these limits are exceeded, device functional operation is not implied, damage may occur and reliability may be affected.

► Electrical Characteristics (TA=25°C Unless otherwise specified)

Symbol	Parameter	Conditions	Min.	Тур.	Max.	Units
V _{RWM}	Reverse Working Voltage	Any I/O to Ground			5.0	V
V _{BR}	Reverse Breakdown Voltage	IT = 1 mA, Any I/O to Ground	6.0			V
Ir	Reverse Leakage Current	$V_{RWM} = 5V$, Any I/O to Ground			1	μΑ
VF	Diode Forward Voltage	IF = 15mA		0.94	1.2	V
XV.	Clausius Valens	$I_{PP} = 1A$, $tp = 8/20\mu s$, any I/O pin to Ground		7.8	9.6	V
VC	Vc Clamping Voltage	$I_{PP} = 4A$, tp =8/20 μ s, any I/O pin to Ground		12	15.0	V
I_{PP}	Peak Pulse Current	$tp = 8/20 \mu s$			4	A
C _J Junction Capacitance	Landing Constitution	$V_R = 0V$, $f = 1MHz$, between I/O pins		0.1	0.3	pF
	$V_R = 0V$, $f = 1MHz$, any I/O pin to Ground		0.45	0.8	pF	

Junction capacitance is measured in VR=0V,F=1MHz

Symbol	Parameter	
V _{RWM}	Working Peak Reverse Voltage	
V_{BR}	Breakdown Voltage @ IT	
$V_{\rm C}$	Clamping Voltage @ IPP	
I_{T}	Test Current	
Irm	Leakage current at VRWM	
Ірр	Peak pulse current	
Co	Off-state Capacitance	
C_{J}	Junction Capacitance	





^{*}Other voltages may be available upon request.

^{1.} Non-repetitive current pulse, per Figure 1.




> Typical Characteristics





Pulse Waveform


Non-Repetitive Peak Pulse Power vs. Pulse Time



Clamping Voltage vs. Peak Pulse




> Typical applications



DUAL USB PROTECTION FOR ESD

ESD protection for USB port



ESD protection for VGA port




Package Information (SOT-363)

Mechanical Data


Case: SOT-363

• Case Material: Molded Plastic. UL Flammability



Dim	Millimeters		
ווווע	MIN	MAX	
A	2.00	2.20	
В	1.15	1.35	
С	0.90	1.10	
D	0.15	0.35	
G	0.65BSC		
Н		0.10	
J	0.08	0.15	
K	0.15	0.35	
N	0.20REF		
S	2.15 2.45		

Recommended Pad outline



Ordering Information

Part Number	Description	Quantity
PAE0514FGJ	SOT-363 Reel	3000 pcs



DISCLAIMER

- The information in this document and any product described herein are subject to change without notice and should not be construed as a commitment by Paceleader, Paceleader reserve the right to make changes to the information in this document.
- Though Paceleader make effort to improve product quality and reliability, Product can malfunction and fail due to their inherent electrical sensitivity and vulnerability to physical stress, it is the responsibility of the customer, when utilizing Paceleader products, to comply with the standards of safety in making a safe design for entire system and to avoid situation in which a malfunction or failure., In developing a new designs, customer should ensure that the device which shown in this documents are used within specified operating ranges.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by Paceleader for any infringements of patents or other rights of the third parties which may result from its use.